

# STAX®



## SRS-X1000 | Earspeaker (SR-X1) + Amplifier (SRM-270s) A Premier Electrostatic Earspeaker System

### The Ultimate Entry into Electrostatic Sound

Designed for audiophiles eager to delve into the world of electrostatic earspeakers without compromise, the SRS-X1000 stands as a beacon of innovation and quality. As the successor to our long-standing SRS-3100 electrostatic audio system, it pairs the brand new SR-X1 earspeakers with the newly developed SRM-270S driver unit, setting a new benchmark for entry-level electrostatic audio system.

**SR-X1 Earspeakers:** Offering a pure and immersive sound experience with:

- **Wide Frequency Response:** Ranging from DC to 35,000Hz for full-spectrum audio reproduction.
- **Minimal Distortion:** Harmonic distortion of 0.01% or less ensures crystal-clear sound.
- **Flexible Installation:** PARALLEL OUT terminals facilitate easy incorporation into your existing audio system, whether for music enjoyment or enhancing movie experiences at your desktop or bedside.

#### SR-X1 (Earspeaker)

- **Type :** Push-pull electrostatic circular speaker, rear-opening enclosure
- **Unit Shape :** Medium-sized circular
- **Fixed electrodes:** High-precision etched electrodes
- **Playback frequency range:** 7-41,000Hz
- **Capacitance:** 110pF (including attached cable)
- **Impedance:** 145kΩ (at 10kHz/including 2.5m attached cable)
- **Sound pressure sensitivity:** 101dB/100Vr.m.s. input/1kHz
- **Bias voltage:** 580V DC
- **Cable conductor:** OFC
- **Cable shape :** Parallel 6-core, wide low capacitance cable, 2.5m
- **Earpads:** Genuine sheepskin leather (skin contact area), artificial leather (attachment area)
- **Weight:** 234g (main unit only)

**SRM-270S Driver Unit:** The heart of the SRS-X1000, featuring:

- **Enhanced Heat Dissipation:** A 3mm-thick front aluminum panel and a larger aluminium extrusion case for effective heat management.
- **High-Grade Connectivity:** RCA pin jacks and a 3mm-thick front aluminium panel ensure a pristine connection.
- **Low Noise FET:** Selected for the First Stage amplifier, paired with a refined emitter follower circuit in the Output Stage for unparalleled clarity.
- **Compact Chassis:** Easy for placement, transportability and aesthetic appeal

#### SRM-270S (Driver unit)

- **Frequency response:** DC to 35,000Hz/+0, -3dB
- **Harmonic distortion:** 0.01% or less/1kHz 100V r.m.s.
- **Amplification:** 58dB (800 times)
- **Maximum output voltage:** 280V r.m.s./1kHz
- **Input impedance:** 25kΩ
- **Input terminals:** RCA x 1
- **Output terminal:** Parallel out x 1
- **Bias voltage:** 580V DC
- **Power supply:** AC adaptor included
- **Power consumption:** 12VDC/500mA
- **External dimensions:** 132(W)×38(H)×153(D)mm (excluding protruding parts)
- **Weight:** 540g

#### Your Gateway to Unprecedented Sound

The SRS-X1000 embodies a perfect fusion of tradition and innovation, offering an accessible yet uncompromised entry into the elite world of electrostatic earspeaker audio systems. Whether you're a long-time audiophile or exploring high-fidelity sound for the first time, the SRS-X1000 provides an unparalleled listening experience.

Discover the richness and depth of your favorite music or cinematic audio like never before. Traversing the delicate whispers to the powerful crescendos, the SRS-X1000 will elevate your auditory journey to new heights.